



Philips Lighting Company

MATERIAL SAFETY DATA SHEET

Revision: 7/06

PRODUCT: ALTO™ Fluorescent Lamp T12 and T8 Halo-Phosphors

SECTION 1: MANUFACTURER

Manufacturer's Name and Address: Philips Lighting Company
A division of Philips Electronics
North America Corporation
200 Franklin Square Drive
Somerset, New Jersey 08875

Emergency Telephone No.: (800) 424-9300 CHEMTREC
(732) 563-3197

Other Information Calls: (732) 563-3488

SECTION 2: HAZARDOUS INGREDIENTS

	OSHA (PEL) mg/m ³	ACGIH (TLV) mg/m ³ TWA	% by Wt.
<u>Inert Ingredients (Glass, Aluminum, etc.)</u>			Approx 97%
Phosphor Powder			Approx 3%
Nuisance Dust	15	10	
Fluorides* (as F)		2.5	Approx .01%
Antimony*(7440-36-0)	.5	.5	Approx .01%
Manganese*(7439-96-5)	.2	.2	Approx .02%
Mercury(7439-97-6)	.1	.025	Less than 20 ppm

*These materials are tightly bound within the crystal matrix of the phosphor (Calcium Phosphate).



A division of
Philips Electronics North America Corporation

200 Franklin Square Drive
P.O. Box 6800
Somerset, NJ 08875-6800
Tel: 732.563.3000

SECTION 3: CHEMICAL/PHYSICAL DATA

Not applicable. This item is a light bulb 18" to 8' long, 1.0 to 1.5 inches in diameter. The bulb is glass, the base is a coated aluminum. The coating is inert.

SECTION 4: FIRE AND EXPLOSION DATA

FIRE AND EXPLOSION DATA NOT APPLICABLE -- under extreme heat, glass envelope might melt or crack.

SECTION 5: REACTIVITY DATA

Stability: Lamp is stable.
Polymerization: Not applicable.
Incompatibility: Glass will react with Hydrofluoric Acid.

SECTION 6: HEALTH HAZARD DATA

Not applicable to the intact lamp. Breakage of the lamp may result in some exposure to the phosphor powder dust and to a very little amount of elemental mercury vapor. No adverse affects are expected from occasional exposure to broken lamps, but as a matter of good practice, prolonged or frequent exposure should be avoided through the use of adequate ventilation during disposal of large quantities of lamps.

EMERGENCY FIRST AID: NORMAL FIRST AID PROCEDURE FOR GLASS CUTS IF SUCH OCCUR THROUGH LAMP BREAKAGE.

SECTION 7: PRECAUTIONS FOR SAFE HANDLING AND USE

Normal precautions should be taken for the collection of broken glass.

Waste Disposal Method: At the end of rated life, when this lamp is removed from service, it will be subjected to the current Toxic Characteristic Leaching Procedure (TCLP) prescribed by the

Environmental Protection Agency. This test is used to determining whether an item is a hazardous waste or a non-hazardous waste under current E. P. A. definition. Philips Lighting will provide the test data on request. This result will allow the generator to evaluate all of the disposal options, which may be available in the particular state in which the generator's facility is located. The generator should check with federal, state and local officials for their guidance. In most states ALTO lamps are considered non-hazardous subtitle D waste. Philips encourages recycling of its products by qualified recyclers.

SECTION 8: CONTROL MEASURES

Respiratory Protection: Appropriate dust mask should be used if large quantities of lamps are being broken for disposal.

Ventilation: Avoid inhalation of any airborne dust. Provide local exhaust when disposing of large quantities of lamps.

Hand and Eye Protection: Appropriate hand and eye protection should be worn when disposing of large quantities of lamps or handling broken lamps.

SECTION 9: REGULATORY INFORMATION

As a product these mercury containing lamps being shipped in the manufacturer's original packaging are not regulated by air, truck or ocean shipment. As a waste, spent ALTO fluorescent lamps maybe regulated in various states and local communities. This material safety data sheet does not constitute "knowledge of the waste", in certain jurisdictions. TCLP data will be furnished upon request.